

Specifications 100kVA Powerlink Generator S/N SAU0155/005

Date of Manufacture	2021
Prime Rating kVA	100
Make	Powerlink
Model	WPS100S-AU
Serial No.	SAU0155/005
Engine Make	Perkins
Engine model	1104C-44TA
Engine serial	RJ51175*R044970G*
Current Engine Hours	15,685
Cylinders	4
Governor	Mechanical
RPM	1500
Service hours	400
Air filter	AF27942
Fuel filter 1	FF167A
Fuel filter 2	4816636
Oil filter full flow	LF699
Oil capacity	8 Litres
Coolant capacity	13 Litres
Starter Motor 12/24v	Perkins 12v T400268 (3.2KW)
DC Alternator 12/24v	Perkins 12v 65a 2781A306
Fan belt	13A1295
Alternator model	Leroy Somer LSA44.3S5 J 6/4
Alternator serial	764612 003
AVR	R250
Control panel	DSE7420
Main Circuit Breaker	ABB XT1C 160 112-160amp adjustable
Earth Leakage Type	NHP Terasaki RD1DF14BN
Outlets Fitted	3 x 32AMP
Battery	1 x Delkor N100R
Fuel Type	DIESEL
Fuel cons @ 75%	17.1 l/hr
Fuel capacity	550 Litres
Avge noise @ 7m	70bd(a)
Length	2888mm
Width	1165mm
Height	1900mm
Approx wet weight	2500 kgs